



**CAUTION:**

BEFORE INSTALLING FIXTURE, MAKE SURE THE POWER TO THE CIRCUIT IS TURNED OFF AT THE MAIN FUSE BOX / CIRCUIT BREAKER UTILITY BOX.

**Important Safety Instructions:**

• These instructions are provided for your safety. It is very important that they are read carefully and completely before beginning the assembly and installation of this lighting fixture.

• **We strongly recommend that a professional electrician install all direct wire fixtures.**

• THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODES BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.

• The lighting fixture is meant for indoor use. WALL MOUNT ONLY. DRY LOCATIONS ONLY. It must be connected only to 3-wire, single-phase electrical supply systems (provided with ground wire or equivalent protection system).

• This fixture has been rated for up to one (1) 60-watt maximum TYPE G edison base (E-26) incandescent light bulb (not included) or one (1) 4.5 -watt TYPE G edison base (E-26) stretch filament light bulb (included).

To avoid the risk of fire, do not exceed the recommended lamp wattage.

• Save these instructions.

**WARNING:**

• To reduce the risk of fire, electrical shock, or personal injury, always turn off light fixture and allow it to cool prior to replacing light bulb.

• Do not touch bulb when fixture is turned on. Do not look directly at lit bulb.

• Keep flammable materials away from lit bulb.



**STEP ONE:**

- Turn off circuit power.
- Prepare j-box.

**STEP TWO:**

- Per local codes, connect ground wire or jumper from ground to the adapter ring with provided ground screw on back of adapter ring.
- Connect adapter ring to j-box.

**STEP THREE:**

- Make wire connections.

Notes:

SMOOTH WIRE IS HOT WIRE.

Ribbed wire is the neutral wire.

DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OR SAFETY WILL BE COMPROMISED.

**STEP FOUR:**

- Connect sconce to adapter ring with 3 set screws in backplate.

**STEP FIVE:**

- Place ceramic reflector around socket. Apply brass collar to secure ceramic reflector in place.

**BE CAREFUL TO NOT OVER TIGHTEN BRASS HOUSING OR CERAMIC WILL CRACK.**



